

Model 8445 Tri-Channel RJ45/BNC A/B Switch, Manual Operation

INTRODUCTION

The Model 8445 Tri-Channel RJ45/BNC A/B Switch enables access to two devices per each of its three channels. Channel 1 allows access to RJ45 devices 1-A or 1-B. Channel 2 allows access to BNC devices 2-A or 2-B. Channel 3 allows access to BNC devices 3-A or 3-B. All channels are switched simultaneously. The unit supports 8 pins for the RJ45 Cat5e interface, and supports both the center conductor and shield of the BNC interface.

Features:

- Simultaneously switches one RJ45 Channel and two BNC channels locally via a knob located on the front panel
- **RJ45 channel tested for Cat5e compliance**
- Leads switched: All (8) RJ45 pins, plus BNC center conductor and shield
- All ports located on the rear panel: (3) RJ45 female and (6) BNC female
- Packaged in a rugged aluminum enclosure for EMI/RFI protection
- Chassis size approximately 8" W x 2.25" H x 7.25" D
- Four threaded screw holes located on the bottom panel.
- Switching is manually operated. Requires no power.
- Custom length cables are available.



Specifications:

PORT CONNECTORS:

(3) RJ45 (F), category 5e connectors on rear panel
(6) BNC (F) Connectors on rear panel..

CONTROLS:

(1) Rotary Switch on front panel selects A or B.

PINS SWITCHED:

RJ45: All 8 Pins Switched.
BNC: Center Conductor and Shield

POWER: No power required.

ENCLOSURE: Shielded Aluminum Enclosure.

DIMENSIONS: 8"W x 7.25"D x 2.25"H.

WEIGHT: Approximately 2.5 lbs

Order Custom Length Cables for optimum performance!

Model 8445 Application

