

## Model 9455SH Dual Channel RJ45 Cat5e A/B Switch, Manual, Simultaneous Switching, Rackmount

- All Ports Are Shielded RJ45 Connectors

### INTRODUCTION:

The Model 9455SH is a dual-channel RJ45 A/B Switch. Both channels switch to A or B simultaneously. Each of the two channels reroutes data from its COMMON port to its A or B port, depending on switch position. The unit supports all 8 pins of the RJ45 Cat5e interface.



### FEATURES:

- Each channel allows quick connection to any one of two devices from one COMMON device.
- **Rated for 10/100/1000 Base-T networks (Up to Cat 5e).**
- **All ports are shielded RJ45 connectors.**
- All 8 pins of the RJ45 interface are switched.
- Transparent to data speed and format.
- Simultaneously switches both channels via front-panel rotary switch.
- High quality sealed switch with self-wiping precious metal contacts.
- Eliminates the need to plug and unplug cables.
- No external power is required.
- Rackmount configuration.
- Attractive anodized black box packaging provides EMI/RFI shielding.
- Lifetime guarantee.
- Custom length Cat5e cables available for your switch application.

### SPECIFICATIONS:

**PORT CONNECTORS:** (3) Shielded RJ45 female connectors labeled A, B, and COMMON, for Channel 1, and (3) RJ45 shielded connectors labeled A, B, and COMMON, for Channel 2.

**FRONT PANEL CONTROLS:** (1) Rotary switch on front panel selects A or B for both channels, simultaneously.

**POWER:** No power required. Manually operated.

**DIMENSIONS:** Rackmount 19" W x 1.75" H x 8" D. (48.3 x 4.4 x 20.3 cm)

**WEIGHT:** Approximately 2.0 lbs. (0.9 Kg)

**Order  
Custom Length  
Cat5e Cables for  
Optimum Performance!**

